

**JERROLD**INTRODUCES THE FIRST OF THE**NEW GIBRALTAR SERIES****SOLID-STATE TV/FM AMPLIFIERS**

MODEL 3440



MODEL 3440

**DESCRIPTION**

No more tube worries. Equip your system with a new Model 3440 and enjoy the maintenance-free service provided by this solid-state equivalent of tube-type amplifiers twice its size. Model 3440 has an excellent output capability and provides high gain for both the TV and FM bands. These features, combined with a low noise figure and flat response, deliver the quality and punch to supply any small system.

**Ideal for small systems****FEATURES**

- **COMPLETELY SOLID-STATE**

For long-life maintenance-free service.

- **GAIN**

23 db average for TV band.  
21.5 db average for FM band.

- **HI OUTPUT CAPABILITY**

lo-band 45 dbj\* (180,000 microvolts at 75 ohms) per channel for 3 channels at 0.5% cross-mod.

hi-band 43 dbj (145,000 microvolts at 75 ohms) per channel for 4 channels at 0.5% cross-mod.

- **LO NOISE FIGURE**

4.8 db average for lo-TV band.  
6.0 db average for hi-TV band.

- **FLAT RESPONSE**

1.5 db max. across entire bandwidth (54-108 mc, 174-216 mc).

- **SWITCH-SELECTED 75 OR 300-OHM INPUT**

- **75-OHM TV/FM OUTPUT**

\*0 dbj=1,000 microvolts across 75 ohms.

DISTRIBUTOR SALES DIVISION  
15th and Lehigh Ave. • Philadelphia, Pa. 19132

The Nation's Foremost Manufacturer and Supplier of Television Distribution Systems

**JERROLD**  
ELECTRONICS